



AX-X3 Auxiliary contact

1. Compliant standards

IEC60947-5-1

2. Compliant certification

CE, RoHS

3. Major function

To be assembled with the circuit breaker to achieve long-distance signal indication for the open/close status of the circuit breaker

4. Technical data

Rated operating currents under different working voltages:

Table 1

Utilization category	Rated operating voltage V	Rated operating current A
AC-12	AC 415	3
	AC 240	6
DC-12	DC 130	1
	DC 48	2
	DC 24	6

Action characteristics: Figure 1 shows the wiring diagram for auxiliary contacts. When the auxiliary contacts are open, terminals 11 and 12 are connected; When the auxiliary contacts are closed, terminals 11 and 14 are connected.

Life: Operating life of auxiliary contacts is 10000 cycles.




Figure 1

5. Assembly and installation of the product

AX-X3 can be assembled with NXB-125, NXB-125G series circuit breaker, with the assembly diagram shown below:

Figure 2



After AX-X3 is assembled with the circuit breaker, mount them on the TH3.5-7.5 steel mounting rail.



4. Dimensions and installation sizes

Figure 3

