

LED Turn Light

T series

INSTRUCTION MANUAL

Thank you for purchasing Hanyoung Nux products. Please read the instruction manual carefully before using this product, and use the product correctly. Also, please keep this manual where you can view it any time.

HANYOUNG NUX

HANYOUNGNEX CO.,LTD

28, Gilpa-ro 71beon-gil,
Michuhol-gu, Incheon, Korea
TEL : +82-32-876-4697
http://www.hynux.com

ML0503KE200903

Safety information

Please read the safety information carefully before the use, and use the product correctly. The alerts declared in the manual are classified into Danger, Warning and Caution according to their importance.

⚠ DANGER	Indicates an imminently hazardous situation which, if not avoided, will result in death or serious injury
⚠ WARNING	Indicates a potentially hazardous situation which, if not avoided, could result in death or serious injury
⚠ CAUTION	Indicates a potentially hazardous situation which, if not avoided, may result in minor injury or properties damage

⚠ DANGER

- Be sure to turn off the power before wiring as there is electric shock danger.

⚠ WARNING

- Be sure to check the power voltage before installing the product, as overvoltage may cause breakdowns.
- Do not change the specifications of the product or assemble parts of other products, as doing so may cause breakdowns.
- Be sure to insulate the unused wire terminals.
- Since this product is not equipped with a power switch and fuse, install them separately on the outside
- If there is a possibility that a breakdown or abnormality of this product may lead to a serious accident to the system, install an appropriate protection circuit on the outside.

⚠ CAUTION

- This product is for indoor use only. Use it in places without water.
- Wire correctly referring to the connection diagram, as wrong wiring may cause breakdowns or light failures.
- Any use of the product other than those specified by the manufacturer may result in personal injury or property damage.
- Do not pull the wires that come out of the product strongly, as it may cause disconnections, short circuits, or other breakdowns.
- Excessive shocks to the product may cause breakdowns or damages.

Suffix code

Model	Code	Content
T	☐ - ☐ ☐ ☐ ☐ - ☐ ☐	Turn light
Dimensions	060	Ø 60
	084	Ø 84
	100	Ø 100
	150	Ø 150
Cap shape	P	Round cap ※except Ø150 model
	F	Square cap
Functions	A	Rotating continuous light
	F	Rotating continuous light / Buzzer
Power voltage	D12	12 V d.c.
	D24	24 V d.c.
	A11	110 - 220 V a.c.
Cap Colors	R	Red
	Y	Yellow
	G	Green
	A	Blue (only with Ø 84 model)
Mount	D	Direct installation type (basic type)
	M	Supporter installation type ※ only with Ø60/Ø84 models with rotating continuous light

Connection diagram

The connection diagram for each power voltage is as follows.
The buzzer with built-in buzzer is connected to the power line.

Power voltage	Wiring color
12 V d.c.	White (+), Black (-)
24 V d.c.	
110 - 220 V a.c. 50/60Hz	White - Black (when using 110 - 220 V a.c.)

Installation method

Indoors			Outdoors		

- This product is manufactured with a general structure for indoor use. You can install it in any direction when using it indoors.
- When using it outdoors, install it in vertical forward direction in places with limited rainwater infiltration.
- If possible, install it in a places with low moisture, dust, vibrations or impacts.

Dimension and panel cutout

[Unit : mm]

Model	Dimension and panel cutout	
T060-P ☐ - ☐ - ☐ - ☐ - ☐ - ☐ T060-F ☐ - ☐ - ☐ - ☐ - ☐ - ☐		
T060-P ☐ - ☐ - ☐ - ☐ - ☐ - ☐ T060-F ☐ - ☐ - ☐ - ☐ - ☐ - ☐		

T084-P ☐ - ☐ - ☐ - ☐ - ☐ - ☐ T084-F ☐ - ☐ - ☐ - ☐ - ☐ - ☐		
T100-P T100-F		
T150-F		

Supporter dimension

※ Optional configuration

Shape	Using model	Dimension and panel cutout	
	T060		
	T084 T100		
	T084 T100		
	T100		
	T060 T084		
	T060 T084		

T series

NEW

Thông số kỹ thuật

Mã hàng	T060 / T084	T060 / T084	T060 / T084 T100 / T150	T060 / T084 / T100	T060 / T084 T100 / T150	T060 / T084 / T100
Hình dạng ngoài	 T060 T084 T100 T150					
Hình dáng	Nắp tròn, có giá đỡ	Nắp bằng, có giá đỡ	Nắp bằng	Nắp tròn, gắn trực tiếp	Nắp bằng, gắn trực tiếp	Nắp tròn, gắn trực tiếp
Chức năng	Xoay sáng liên tục				Xoay sáng liên tục, còi báo	
Điện áp nguồn	● 12 V D.C : 0.08 A, ● 24 V D.C : 0.06 A, ● 110 - 220 V A.C : 0.03 A				● 12 V D.C : 0.09 A, ● 24 V D.C : 0.07 A, ● 110 - 220 V A.C : 0.04 A	
Chu kỳ quay	180 ± 15% lần / 1 phút					
Âm lượng còi báo	-				Khoảng 80 dB	
Vật liệu nắp	Nhựa polycarbonate (PC)					
Thân	Nhựa ABS					
Màu sắc nắp	Đỏ, vàng, xanh lá, xanh dương					
Cấp độ bảo vệ	IP54					

Đèn báo hiệu

Mô đun
Đèn báo hiệuSản phẩm mới
Đèn bằng
điều khiểnĐèn báo
Gắn tườngĐèn báo hiệu
xoay

Đèn cảnh báo

Mã đặt hàng

Mã hàng	Ký hiệu					Thông tin
T	□	□	□	□	□	Đèn báo hiệu dạng xoay
Kích thước	060					Ø 60
	084					Ø 84
	100					Ø 100
	150					Ø 150
Hình dạng nắp	P					Nắp tròn ✕ Ngoại trừ Ø150
	F					Nắp bằng
Chức năng	A					Đèn xoay
	F					Đèn xoay - Còi báo
Điện áp nguồn	D12					12 V D.C
	D24					24 V D.C
	A11					110 - 220 V A.C
Màu sắc nắp	R					Đỏ
	Y					Vàng
	G					Xanh lá
	A					Xanh (Áp dụng cho Ø 84)
Bệ đỡ	D					Loại lắp trực tiếp (cơ bản)
	M					Loại chân đế ✕ Áp dụng cho Ø60, Ø84 Xoay, sáng liên tục, còi báo



www.npower.com.vn

Tài liệu được tổng hợp bởi đội ngũ kỹ thuật của NPOWER

Bản quyền nội dung thuộc về công ty Hanyoung Nux

Powered by NAVITECH | www.navitech.co